

Listening in English on Short Wave in North West Europe

weak signal good signal strong

WINTER 2015-16

China Radio International (CRI): Kings of International Broadcasting to Europe

05 GMT	06	07	08	09	10	11	12	13	14	15	16	17	18	19	20	21	22	23
Xian 292 500kW 17.73				KAS 308 500kW 17.65			URU 308 500kW 13.79 China			KAS 308 500kW 9.525	KAS 298 500kW 9.875	BEI 318 500kW 6.10 China			KAS 308 500kW 9.60 China			
KAS 269 500k to Mid East +N Afr 17.51 China to Afr		KAS 269 500kW to ME+N Afr 17.67 China to Africa		URU, Urumqui NW China 308 500kW 17.57		CER in Albania 310 150kW 13.665		KAS 308 500kW 13.67	KAS 308 500kW 13.71	KAS 298 500kW 9.435	KAS 308 500kW 9.435			KUN 283 500kW 9.44 Afr	KAS 308 500kW 7.415 China			KAS 308 500kW 7.35 China
		KAS, Kashi in far west China 308 500kW 17.49 China to Europe in English					URU 308 500kW 17.49		URU 308 500kW 9.795		URU 270 500kW 7.42 ME		BEI 318 500kW 7.405	KAS 269 to 2100 7.295 ME	CER 310 150kW to UK 7.285 China from Albania			
CER to Egypt 140 150kW 7.22	11.75			CER in Albania 310 150kW							KAS 294 500kW 7.255 China				CER 310 150kW 5.96 China from Albania			

All India Radio is a powerful signal in the evenings →

BGL, Bangalore 325 500kW
11.67 All India Radio
DEL, Delhi 282 250kW
9.445 India to Africa

BGL 325 500kW
11.67 All India Radio
BGL 325 500kW
9.445 All India Radio

Everything else in English with good or strong reception - Romania, Iran, Turkey, Vietnam & Vatican Radio all have strong signals

05	06	07	08	09	10	11	12	13	14	15	16	17	18	19	20	21	22	23
TIG 97 300kW to Australia 21.58 Romania	GAL 100 300kW to Australia/DHA 260 250kW 17.78 Romania	SMG 107 100kW starts Latin then news to Mid East (not Su) 15.595 Vatican	JISS in France 175 500kW 15.53 D Welle		KAM, Kamalabad 105 500kW to India 21.51 Iran	KAM 112 500kW to India 17.56 Iran	GAL 165 to E Africa 17.765 Romania		SAO 126 100kW 17.885 voa	SAO 100 100kW 17.895 voa	SMG 144 250kW 17.895 VOA to Africa							
Botswana 350 100kW 15.58 VOA to Africa							TIG 307 300kW 15.46 Romania		Botswana 10 100kW 15.58 VOA to Africa						SMG 184 250kW 15.58* VOA	Greenville 94 250kW 15.58* VOA		
	MEY 328 250kW 15.255 Channel Africa				SMG 319 100kW 15.595 Su: Vatican		TIG 165 300kW to East Africa 15.15 Romania			SMG 90 125kW India 15.775 Vatican		MEY 340 250kW 15.235 Channel Africa						
Madagascar 300 250kW 15.405 D Welle	SMG 184 250kW to Africa 11.625 Vatican	RAN 35+325 100kW 9.765 New Zealand							THU 315 100kW 15.14 Oman									
Madagascar 258 13.765 Vat'n	SMG 210 250kW to Africa 9.66 Vatican																	
DHA,UAE 315 250kW 13.64 Japan	TIG 307 300kW 7.345 Rom	NAU 270 100kW Bible Voice Sa/Su: 7.22 God																
ISS in France 155 500kW 9.77 Japan	SMG 4+326 350k Mass 6.07 Vatican			SHP, Shepparton 355 100kW 12.065 Australia														
				NAU, Nauen near Berlin 230 100kW 6.095 M,Th,F: Transport Radio														
				NAU 240 100kW 6.095 Sa/Su: Mighty KBC Radio Music in English and Dutch						EMR, Emirler 310 500kW 12.035 Turkey								

* In December and January, few signals over 9 MHz are audible after 1900 GMT

05	06	07	08
MEY 19 E Africa 12.095	MEY 335 100kW 12.095	MEY, Meyerton, S Africa 328 250kW 17.83 BBC	
	Madagascar 315 250kW 17.64	17.64 E Africa	
ASC 102 250kW 7.445	ASC 65 250kW 9.46	ASC, Ascension Island 65 250kW 12.095	
Ascension Is to Ghana 27 250kW 6.005 BBC	ASC 27 250kW to Ghana 11.77		
ASC 65 Nigeria 5.875	ASC 65 125kW 9.915 BBC to Nigeria		

← BBC World Service →
Usually faint mutterings from transmitters not aimed at Europe
NB All signal strengths vary day to day

13	14	15	16	17	18	19	20	21	22	23
NAK, Thailand 290 250kW 15.31 BBC		MEY 20 100kW rarely audible 15.42 BBC	ASC 27 125kW 15.42+17.83	ASC 27 125kW 15.40 BBC to West Africa			ASC 27 125kW 12.095			
SNG 13+135 250kW 9.74 BBC Asia		SNG, Singapore 315 100kW 9.41 BBC to Asia	MEY 20 100kW 15.42 BBC	DHA in UAE 220 250kW 9.41 BBC to E Africa						
		MDC, Madagascar 315 250kW 12.095 to East Africa	Madagascar 315 250kW hit by interference 1730-1830 7.445 BBC to East Africa							
		SNG, Singapore 320 250kW 7.465 BBC to South Asia	ASC 65 250kW 17.78+17.83	WOF, Woofferton in Shropshire 170 250kW 9.915 BBC to West Africa						
		SLA in Oman 335 250kW 6.195 to Iran /Mid East		ASC 65 250kW starts 1800 6.195						

Digital Short Wave (DRM) - You need a special set - The BBC provides one hour of DRM to Europe in the morning

05 GMT	06	07	08	09	10	11	12	13	14	15	16	17	18	19	20	21	22	23
	French 6.04 Rom	RAN in New Zealand 35+325 50kW - very faint M-F: 11.69 NZ																
	English 9.60 Rom		NAK in Thailand 290 100kW - aimed at Asia 17.79 BBC															
	Russian 5.94 Rom	German from Romania 6.02 Rom																
		WOF, Woofferton in UK 114 100kW 3.955 BBC																

NAK in Thailand 290 100kW
5.845 BBC digital weak from Thailand
Abuja 100kW in English
15.12 Nigeria
Delhi 312 50kW in English
7.55 All India R in Hindi
TIG 307 English
TIG 307 in German
TIG 37 in Russian
5.93 Rom
TIG 307 English
7.35 Romania
TIG Italian
7.405 Rom
ISS ND 1kW very weak signal 24hrs
3.965 France digital